

DATA SHEET.

12Vdc CONSTANT VOLTAGE SWITCH MODE POWER SUPPLY

Based on an evaluation of your project, eLumanation will suggest the appropriate power supply(ies) to best suit your installation's requirements. Utilizing any power supply(ies) that are not approved by eLumanation voids the eLume LED product's warranty. To utilize the power supplies in a remote location at a distance further than the wiring provided, ensure that you utilize a larger gauge cable to avoid any voltage drop. (>#16AWG)

*** ALL ELUMANATIONS POWER SUPPLIES ARE FULLY UL CERTIFIED & ARE ACCOMPANIED WITH A (1) YEAR WARRANTY ***



MODEL :	E-PS/12VDC/36W	E-PS/12VDC/60W	E-PS/12VDC/80W	E-PS/12VDC/120W
OUTPUT VOLTAGE :	12 Vdc	12 Vdc	12 Vdc	12 Vdc
RATED CURRENT :	3 A	5 A	6.6 A	10 A
CURRENT RANGE :	0 ~ 3 A	0 ~ 5 A	0 ~ 6.6 A	0 ~ 10 A
MAX POWER LOAD :	36 WATTS	60 WATTS	80 WATTS	120 WATTS
INPUT VOLTAGE :	90 ~ 240 Vac	90 ~ 240 Vac	90 ~ 240 Vac	90 ~ 240 Vac
FREQUENCY RANGE :	50 ~ 60 Hz	50 ~ 60 Hz	50 ~ 60 Hz	50 ~ 60 Hz
DIMENSION :	35*100*56 mm	33*120*56 mm	38*124*62 mm	38*166*62 mm

+ 10 A, 120W POWER SUPPLY DETAILS AVAILABLE UPON REQUEST.

CONTACT INFO.

www.elumanation.com
416.225.6400

1621-3 McEwen Drive, Whitby.
ON, Canada. L1N 9A5